



Pin Configuration for MSD600C 5.1

Page 1/1

DK-Audio A/S
 Marielundvej 37 D
 2730 Herlev, Denmark
info@dk-audio.com
www.dk-audio.com/

AES/EBU Input			
<i>25-Pole DSUB</i>			
Input			
<i>AES/EBU 1</i>	<i>Hot</i>	<i>Pin 9</i>	
	<i>Cold</i>	<i>Pin 21</i>	
	<i>GND</i>	<i>Pin 22</i>	
<i>AES/EBU 2</i>	<i>Hot</i>	<i>Pin 10</i>	
	<i>Cold</i>	<i>Pin 23</i>	
	<i>GND</i>	<i>Pin 22</i>	
<i>AES/EBU 3</i>	<i>Hot</i>	<i>Pin 20</i>	
	<i>Cold</i>	<i>Pin 7</i>	
	<i>GND</i>	<i>Pin 8</i>	

Power, RS232 & I2C			
<i>9-Pole DSUB</i>			
<i>+Vcc</i>	<i>12-15V</i>	<i>Pin 4</i>	
<i>Power ground</i>		<i>Pin 5</i>	
<i>I2C</i>	<i>IRQ</i>	<i>Pin 8</i>	
	<i>SDA</i>	<i>Pin 7</i>	
	<i>SCL</i>	<i>Pin 6</i>	
<i>RS232</i>	<i>TX</i>	<i>Pin 2</i>	
	<i>RX</i>	<i>Pin 3</i>	
<i>GND</i>		<i>Pin 1</i>	

VGA			
<i>15-Pole DSUB</i>			
<i>GND</i>		<i>Pin 5,6,7,8,10</i>	
<i>H-sync</i>		<i>Pin 13</i>	
<i>V-sync</i>		<i>Pin 14</i>	
<i>Red</i>		<i>Pin 1</i>	
<i>Green</i>		<i>Pin 2</i>	
<i>Blue</i>		<i>Pin 3</i>	